


ELECTRONICS CO.

EMERGENCY VEHICLE SOUND, LIGHTING & EQUIPMENT

2015 Ford F-150 Contour Console 901-0135A

Installation Instructions



Parts List

Part #	Description	Qty
901-0135A	2015 FORD F-150 LT7600 CONTOUR CONSOLE	1
801-0614A	CONSOLE PS POCKET	1
801-0675A	CONSOLE DS POCKET (OPTIONAL)	1


Hardware List

Line #	Description	Qty
1	WASHER 1/4"	8
2	NUT NYLOCK 1/4"	8
3	# 6 TAP SCREW BLACK FOR FACEPLATES	10
4	1/4-20 x 5/8" Hex Bolt	8
5	3/8" X 1 3/4" Self Tapping (401-0228)	4
	HARDWARE BELOW IS FOR PS SIDE POCKET (OPTIONAL DS)	
6	BOLT CARRIAGE 1/4-20 X 5/8"	6 EACH
7 *	WASHER 1/4"	6 EACH
8	NUT NYLOCK 1/4"	6 EACH

Installation Instructions

Step 1

Remove floor plate/covers and remove existing hardware leaving any electronics and wiring a lone. Keep existing hardware for later steps.



Step 2 Unplug and Remove the 12V and USB outlets from the vehicle. Caution! Do not use excessive force.







Step 3 Insert both the 12V outlet and the USB port into the designated spots located in the front corner of the 901-0135A console.




Step 4
Use 8 1/4-20 x 5/8" hex bolts, 1/4-20 washer as well as 1/4-20 nyloc nuts to bolt in the inside mounting brackets which will be bolted to the vehicle in a later step. Don't tighten all the way, back bracket hardware will have to be used again.
Also, use 6 1/4-20 x 5/8" carriage bolts, 1/4-20 washer and 1/4-20 nyloc to mount the PS side pocket on. (OPTIONAL DS pocket is installed identical





Step 5
Remove back and front bracket hardware to align rear and front side covers and re-use hardware to tighten components. Tighten all hardware to make sure every part of the console is secure.





Step 5
Place the console into vehicle aligning the mounting bracket holes with the designated mounting holes in the vehicle. Reuse the mounting hardware removed from the vehicle in step 1. DO NOT TIGHTEN MOUNTING HARDWARE.





Step 6
Align console with the front dash and make sue console placement is aligned with all parts and centered properly.
Reconnect wiring to the 12V and USB ports which were moved to the side of the console. Tighten all mounting hardware to secure console in place and tighten any remaining hardware that may have been missed.





Step 7 Installation of 901-0135A console is complete.

WARRANTY

D & R Electronics warrants its new products to be free from defects in material and workmanship, under normal use and service, for a period of one year on parts replacement, and one year on labor,

This warranty applies only to original purchasers acquiring the product directly from D&R Electronics, or its authorized dealers. Warranty will not be recognized without proof of purchase or bill of sale. This warranty is not transferable. The warranty begins on the date of delivery to the first user/purchaser. This warranty shall not apply to products which must be repaired due to normal wear and tear, negligence, improper installation, abuse, misuse, or which have been altered or modified at a facility other than D & R Electronics, or its authorized depot center. Units proved to be defective within the warranty period, based on an examination by D&R Electronics, will be replaced or repaired at D & R Electronics' option. This warranty does not cover travel expenses or labor charges for removal or installation. Lamps, flash tubes, batteries or other items considered consumables are not covered under warranty. This warranty is in lieu of all other express warranties. D&R Electronics makes no other warranties, expressed or implied, than the express warranties contained herein.

PRODUCT RETURN POLICY

In order to provide you with faster service, product returns for repair or replacement, must have a **Return Goods Authorization Number (RGA number)**. Please contact our company to obtain a RGA number before you return the product to D & R ELECTRONICS. Write the RGA number clearly on the package. Be sure you use sufficient packing materials to avoid damage to the product being returned while in transit.

D&R Electronics Ltd.

CANADA

8820 George Bolton Pkwy. Bolton, ON L7E 2Y4

Tel.: (905)951-9997 Fax: (905)951-0019 USA

2321 Kenmore Ave. Buffalo, NY 14207

Toll Free 1-800-538-7338

www.dandrelectronics.com